

## Model AL101-1 Indoor Alarm

The Model AL101 accepts a switch contact input and provides an audible alarm signal when the external contact is closed. A red lighted push-button provides the visual alarm indication. The push-button is a momentary switch that, when pressed, mutes the buzzer. The red light remains on until the alarm condition is corrected. The alarm circuit resets automatically. Use Ktech float switches for the alarm input contacts. The relay output contact corresponds to the input alarm contact.

### Electrical Specifications

- 120 VAC, 60 Hz, 85 mA
- Switch input at terminals **4 & 5**
- Relay NO output at terminals **6 & 7**
- Buzzer -- 70 dB @ 3 feet.



Certified to CAN/CSA C22.2 No. 205 and Conforms to ANSI/UL Std. 464

**CAUTION: REFER TO INSTRUCTIONS BEFORE OPERATING ALARMS**

